

DIGITRADIO 100 IR

DAB+ and UKW digital radio with internet radio, Bluetooth audio streaming and extra large display

Colour	EAN	Item no.
black	4019588109575	0010/4957

TOP FEATURES

- DAB+ digital radio
- RDS UKW radio
- favorite memory
- display of clock and date
- two radio alarm timer possible
- Dot-Matrix LCD-display with illumination
- Bluetooth Audio Streaming (Empfang)
- internet radio via WIFI
- external antenna connection
- remote control

STREAMING

- Audio streaming: Yes (UPnP, Bluetooth)

HANDLING/COMFORT

- Favourites programme manager DAB+: 10
- Favourites programme manager FM: 10

POWER CONSUMPTION

- In operation: 5 W
- Power consumption in standby mode with active network connection: 2,36 W
- Standby: 0,86 W

CONNECTIONS

- Audio out analogue (3,5 mm jack): 1
- connector external antenna: 1

AMBIENT OPERATING CONDITIONS

- Humidity: 5 - 90 % relative Luftfeuchtigkeit (nicht kondensierend)
- Ambient temperature: 5 - 35 °C

WLAN

- WLAN: 802.11 a/b/g/n (2,4-GHz- und 5-GHz Band werden unterstützt)

NETWORK & COMMUNICATION

Bluetooth: Yes

OTHER FEATURES

OSD languages: French, German, Dutch, Finnish, English, Italian, Danish, Portuguese, Norwegian, Spanish, Polish, Swedish

BLUETOOTH VERSION & PROFILE

HFP (Hands Free Profile): ja

AVRCP (Audio Video Remote Control Profile): ja

Bluetooth version: 2.1+EDR

A2DP (Advanced Audio Distribution Profile): ja

HSP (Headset Profile): ja

DISPLAY

Resolution (vertical and horizontal): 74 x 45,2

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Internet radio: Yes

Aerial: DAB/FM aerial

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 6 V / 500mA

Type of power supply: Extern

SCOPE OF DELIVERY

DigitRadio 100 IR, FM/DAB antenna, audio connector cable, plug-in power supply, remote control, instruction manual