


# TECHNIRADIO 8

Portable DAB+ / FM radio with voice announcements

| EAN | Colour | Item no. | Weight (Box) | Weight | Device (W x H x D) | Box |
|---|---|---|---|---|---|---|
| 4019588039308 | black/silver | 0000/3930 | 1,37 kg | 900 g | 26 x 21,1 x 10 cm | 33 x 21,5 x 13 cm |

## TOP FEATURES

- DAB+ digital radio
- FM radio (with RDS and PLL)
- Favorites memory slots (3 DAB+/3 FM)
- Backlit LC display
- Date and time display
- Snooze and sleep functions
- Voice announcements (main functions and pressed keys are announced by voice)
- Adjustable equalizer
- Electronic volume control
- Mains and battery operated

## POWER SUPPLY

- Battery operation: Yes
- Non rechargeable battery: 4 x AA
- Nominal voltage: 230 V
- Frequency: 50 Hz
- Mains adapter: DC 6 V / 1,000 mA
- Type of power supply: External

## HANDLING/COMFORT

- Clock: Yes
- Automatic time reset following a power cut: Yes
- Alarm: Yes
- Sleep timer: Yes
- Snooze: Yes
- Favourites programme manager FM: 3
- Favourites programme manager DAB+: 3

## LOUDSPEAKERS

- Output performance: 6 W (RMS)
- Stereo: 2 x 3 W
- Stereo speakers: Yes
- Mono speakers: Yes

## AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

## POWER CONSUMPTION

Standby: 0,3 W

In operation: 6 W

## CONNECTIONS

Audio in/AUX in: Yes

Headphone connection jack (3,5 mm): 1

USB: 1

## OTHER FEATURES

OSD languages: English, German, French, Italian, Dutch, Norwegian

## DISPLAY

Type: LCD

Dimmable: Yes

## FUNCTIONS

MP3 playback via USB: Yes

## RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: Telescopic antenna

## SCOPE OF DELIVERY

TECHNIRADIO 8, plug-in power supply, instruction manual